

List of available commands

command	description	value [x]		value [y]	
ssrecall_ex MIXER:Lib/Scene [x]	Recall Scene (CL/QL series)	0 – 300	0: #000 ... 300: #300	n/a	n/a
ssrecall_ex scene_a [x]	Recall Scene A (TF series)	0 – 99	0: #00 ... 99: #99	n/a	n/a
ssrecall_ex scene_b [x]	Recall Scene B (TF series)	0 – 99	0: #00 ... 99: #99	n/a	n/a
set MIXER:Current/InCh/Fader/Level [x] 0 [y]	Set input channel Fader Level	0 – 47: CL1 0 – 63: CL3 0 – 71: CL5 0 – 31: QL1 0 – 63: QL5 0 – 31: TF1 0 – 39: TF3 0 – 39: TF5 0 – 31: TF-RACK	0: Input Channel 1 ... 71: Input Channel 72	(–32768) – (1000)	–32768: –∞ ... 1000: 10.00
set MIXER:Current/InCh/Fader/On [x] 0 [y]	Set input channel ON/OFF	0 – 47: CL1 0 – 63: CL3 0 – 71: CL5 0 – 31: QL1 0 – 63: QL5 0 – 31: TF1 0 – 39: TF3 0 – 39: TF5 0 – 31: TF-RACK	0: Input Channel 1 ... 71: Input Channel 72	0 – 1	0: OFF 1: ON
set MIXER:Current/InCh/ToSt/Pan [x] 0 [y]	Set input channel To Stereo Pan	0 – 47: CL1 0 – 63: CL3 0 – 71: CL5 0 – 31: QL1 0 – 63: QL5 0 – 31: TF1 0 – 39: TF3 0 – 39: TF5 0 – 31: TF-RACK	0: Input Channel 1 ... 71: Input Channel 72	(–63) – (63)	–63: L63 63 : R63